

Visit www.businessphonespecialists.com
Or call us at 208-523-0006, 208-232-2224
Or 307-733-8700 for assistance.
Email us at sales@businessphonespecialists.com



ASSIGNING A DISALLOWED LIST FOR THE AVAYA IP OFFICE BASIC

Disallowed List Assignment



IP Office Basic Edition - Quick Mode Phone Admin: [Dialing Restrictions and Permissions](#)



Disallowed List Assignment

Use this feature to assign which [disallowed number lists](#) an extension can use.

1408/1416/9504/9508 Phone

- At either of the first two extensions on the system, press **Admin**.
 - To do the above during a call, you may need to press the **PHONE** button to display the **Admin** soft key option. If you access phone administration during a call, only the **IF SPEAKER**, **MUTE** and **HEADSET** buttons still affect the connected call.
- Use the up or down arrow buttons to scroll the display to **System Administration**. When highlighted, press **Select**.
- Use the up or down arrow buttons to scroll the display to **Restrictions/Permissions**. When highlighted, press **Select**.
 - Alternatively, dial # and the [system administration](#) code.
- Use the up or down arrow buttons to scroll the display to **Disallow To**. When highlighted, press **Select**.
- At the **Extension:** prompt enter the extension number for which you want to assign lists.
- At the **List Number:** prompt enter the list entry you want to change by entering 1 to 8.
- The current setting is displayed. The default is 2 (not active), ie. the extension is not associated with the selected list.
 - 1** = Active/Assigned.
 - 2** = Not Active/Not Assigned (the default setting).
 - Alternatively use the left or right arrow icons to toggle through the settings or **Default** to return to the default setting.
- Use the up or down arrow buttons to select another list.
- Exit programming by pressing **PHONE**. Alternatively use the **Back** button to move to another menu.